

EN - CAUTION: Always switch off mains supply before servicing.

Luminaire Installation:

- Shut OFF the power before installing the product.
- Before installing the product check which plugs and screws are best suited for the intended surface
- Mount the bracket on the ceiling.
- Strip the wires, connect the cable with the connector, make sure the cable wires are correct to connect with L, N and ⊕-marked earth wire.
- Mount the hood and tighten it firmly
- Turn on the power and test the luminaire

WARNING: This product must be earthed. If it becomes necessary to re-wire this product please follow these guidelines. Always secure wires in plug terminals carefully. Make sure the cable is firmly located in the cord grip. NEVER connect the green & yellow wire to any terminal other than one marked with the earth symbol

'E' or '⊕'. Regularly inspect all electrical connections and wiring for damage. Any faults should be immediately rectified before further use of this product. Always have the wiring and connections checked by a qualified electrician. In use, ensure all wiring and extension cables are kept clear of any cutting tools, sharp objects and any other potential hazard such as wet floors, chemicals, solvents etc.

NL - LET OP: Schakel altijd de netvoeding uit voordat u onderhoud pleegt.

Armatuur Installatie:

- Schakel de stroom UIT voordat u het product installeert.
- Controleer voordat u het product installeert welke pluggen en schroeven het meest geschikt zijn voor de beoogde ondergrond
- Monteer de beugel aan het plafond.
- Strip de draden, verbind de kabel met de connector, zorg ervoor dat de kabeldraden correct zijn om te verbinden met L, N en ⊕-gemarkeerde aarddraad.
- Monteer de kap en draai hem stevig vast
- Schakel de stroom in en test de armatuur

WAARSCHUWING: Dit product moet geaard zijn. Als het nodig is om dit product opnieuw te bedraden, volg dan deze richtlijnen. Zet de draden altijd zorgvuldig vast in de aansluitklemmen. Zorg ervoor dat de kabel stevig in de snoergreep zit. Sluit de groene en gele draad NOOIT aan op een andere terminal dan een die is gemarkeerd met het aardesymbool 'E' of '⊕'. Inspecteer regelmatig alle elektrische aansluitingen en bedrading op schade. Eventuele gebreken moeten onmiddellijk worden verholpen voordat dit product verder wordt gebruikt. Laat de bedrading en aansluitingen altijd controleren door een gekwalificeerde elektricien. Zorg er tijdens het gebruik voor dat alle bedrading en verlengkabels vrij zijn van snijgereedschap, scherpe voorwerpen en elk ander potentieel gevaar zoals natte vloeren, chemicaliën, oplosmiddelen enz.

Technical Specifications

Supplier item number 5325000300

Dimensions & weight

Product Height (in mm) 100
 Product Width (in mm) -
 Product Length (in mm) 400
 Product Netto weight (in gr) 780

Technical specifications

Luminous Flux (For lightsource) 2000 Lm (@6500K)
 Useful Luminous Flux (For Containing Product) 1300 Lm
 Beam angle measured lumen (luminous flux) 360 degrees
 RGB Yes
 CCT Yes
 Colour Temperature 2700K-6500K
 Colour Rendering (Ra) 80
 Wattage (W - Rated Power) 20W
 Voltage (V) 220-240V AC
 Current (mA) -
 Frequency (Hz) ~50/60 Hz
 Power factor (pf) >0,7
 Pon (on mode power) 20W
 Pnet (network standby power) 0,5W
 Psb (standby power) -
 Energy class (ERP2) F
 Life time (h) - L70B50 15000
 Switches 15000
 Dimmable (Yes/No) Yes, by app only

SMART items:

Frequency Range 2412-2472 MHz
 Antenna Gain 0.8dBi
 Max. Radio Transmission Power 16dBm

IP value 20
 Accessoires -

